


Control Gear for Sunmaster Grow Lamps

Magnetic Ballast Electrical Data

| | |
|-------------------------------|------|
| Lamp Watts (W) | 250 |
| Lamp Current (A) | 3.0 |
| Input Voltage at 50Hz | 230 |
| Circuit Watts (W) | 285 |
| Running Current (A) | 1.55 |
| ta (°C) | 25 |
| Thermal Cut-out | N |
| Capacitor Value (µf) | 30 |
| Capacitor Voltage (V) | 250 |
| Energy Efficiency Index (EEI) | A3 |

Physical Data

| | |
|-----------------------|-------------|
| Dimensions (LxWxH mm) | 245x114x106 |
| Fixings (mm) | 220-228 |
| Weight (kg) | 4.1 |



Ballast Diagram

Revision: 10-06-2013

See page 2 for product notes

Control Gear for Sunmaster Grow Lamps

Notes:

THE UNIT CONSISTS OF BALLAST/IGNITOR AND CAPACITOR

Length of lead A = 1.5m and length of lead B = 3m